

# iKAL 8241L Voyager Mobile Entry Intercom 2G & 3G



- Remote Control of entrance gates.
- Excellent Audio Quality.
- Easy to install. Quick to configure. Only mains wires required.
- Set-up done by simply texting messages from mobile. Change users by text. Its more secure. End User does not have to worry about missing fobs.
- Never miss a caller even when out of the office!
- Controlled access to the gardener, Oil refill truck, plumber... when home-owner away from premises.
- Sends a warning if the gate is left open.
- IP67 waterproof enclosure.
- Receive a warning if credit is running low.
- Response to incoming calls can be disabled.
- Bill Pay or Pre Pay options. 2G/3G/4G SIM

Intercoms	iKAL 8241L
Power	12V DC 2 Amp (supplied)
Number of phone intercom users	5
Dial to open users	200
Method of programming.	SMS Text
Method of operation.	Press the intercom call panel Dial to open (no call cost) and SMS text
Pulse Time	3 seconds (Configurable).
Gate open for fixed period	SMS command. Programmable time period. From a minute to many hours.
Security Settings	4 Digit security code
Number of Inputs	2
SMS Text on gate open/close	Control Phone
Gate Status	SMS text to query if gate open.
Credit Monitor Command	Query credit on the SIM . Sends timed SMS Text with credit amount.
Warning Text	Warning text sent when gate left open
Keeps SIM on the network	Text sent by device to Control Phone every 75 days to add credit.
Multi Button Intercoms	1 to 5 Button
Free Apps available for Android and iPhone	Single gate and Multiple Gate controllers.