

Q: What is different in wiring a Multi Button Intercom?

Wiring a Multi Button Intercom is just the same as wiring a single button Intercom, but there are additional pull-wires(Wires from the buttons). Button 1 pull-wire is wired to S1 on the PCB and Button 2 to S2 on the PCB and so on.

Q: What is different about programming a Multi Button Intercom?

Answer:

- A multi button Intercom will have 3 numbers assigned per button.
- The first 3 numbers Phone 1, Phone 2 and Phone 3 are assigned to button 1, Phone 4,5 and 6 to button 2 and so on. See the table below for this in detail.

PHONE 1	First Number - Button 1
PHONE 2	Second Number - Button 1
PHONE 3	Third Number - Button 1
PHONE 4	First Number - Button 2
PHONE 5	Second Number - Button 2
PHONE 6	Third Number - Button 2
PHONE 7	First Number - Button 3
PHONE 8	Second Number - Button 3
PHONE 9	Third Number - Button 3
PHONE 10	First Number - Button 4
PHONE 11	Second Number - Button 4
PHONE 12	Third Number - Button 4
PHONE 13	First Number - Button 5
PHONE 14	Second Number - Button 5
PHONE 15	Third Number - Button 5
OPEN 1	
OPEN 2	
OPEN 3	
OPEN 4	

- For each button you can program one to three numbers. If you don't require 3 numbers then just program the numbers you want to use.
- See the Installer manual on how to program PHONE numbers in the device.